

Correlated tunneling into a superconductor in a multi-probe hybrid structure

G. FALCI^{1,2,3}, D. FEINBERG³ and F.W.J. HEKKING⁴

¹ *Dipartimento di Metodologie Fisiche e Chimiche (DMFCI), Università di Catania - viale A. Doria 6, 95125 Catania, Italy.*

² *Istituto Nazionale per la Fisica della Materia (INFM), Unità di Catania.*

³ *Laboratoire d'Etudes des Propriétés Electroniques des Solides, Centre National de la Recherche Scientifique, under contract with Université Joseph Fourier, BP 166, 38042 Grenoble Cedex 9, Grenoble, France*

⁴ *Laboratoire de Physique et Modélisation des Milieux Condensés, Centre National de la Recherche Scientifique and Université Joseph Fourier, BP 166, 38042 Grenoble Cedex 9, Grenoble, France*

PACS. 74.50.+r – Proximity effects, weak links, tunneling phenomena, and Josephson effects.

PACS. 74.80.Fp – Point contacts; SN and SNS junctions.

PACS. 75.75.+a – Magnetic properties of nanostructures.

Abstract. – We consider tunneling in a hybrid system consisting of a superconductor with two or more probe electrodes which can be either normal metals or polarized ferromagnets. In particular we study transport at subgap voltages and temperatures. Besides Andreev pair tunneling at each contact, in multi-probe structures subgap transport involves additional channels, which are due to coherent propagation of two particles (electrons or holes), each originating from a different probe electrode. The relevant processes are electron cotunneling through the superconductor and conversion into a Cooper pair of two electrons stemming from different probes. These processes are non-local and decay when the distance between the pair of involved contacts is larger than the superconducting coherence length. The conductance matrix of a three terminal hybrid structure is calculated. The multi-probe processes enhance the conductance of each contact. If the contacts are magnetically polarized the contribution of the various conduction channels can be separately detected.

Superconductor-normal metal (SN) contacts at mesoscopic scale are of primary importance in view of the interplay between coherence effects in the metal and intrinsic coherence of the superconducting condensate which is probed by Andreev reflection [1, 2]. The situation becomes even more interesting with ferromagnetic metals (F). The subgap Andreev conductance tends to be hindered by magnetic polarization [3–5] of the F electrode, since not every electron from the spin up band can find a spin down partner to be converted in a Cooper pair. Recent experiments [6, 7] suggesting a proximity effect in SF junctions are still under debate. More generally, multi-terminal NS structures offer the possibility of manipulating phase coherent transport [8]. An example is the Andreev interferometer consisting of a mesoscopic N sample, made of two arms connected to two S “mirrors” on one side and to a single reservoir on the

other, where electron propagation in N is sensitive to the difference of the phase of the two superconductors. In general the two SN contacts are separated by a distance larger than the superconducting coherence length $\xi = \hbar v_F / \pi \Delta$, Δ being the superconducting energy gap. A dual configuration, consisting in a superconductor connected to two N probe electrodes separated by a distance *smaller* than ξ (see Fig 1.a), with two *independent* reservoirs, was considered in Ref. [9,10]. It has been proposed that correlations between the N probes could be established across the superconductor, by a process where two electrons *each originating from a different N electrode*, are converted in a Cooper pair. Recently, it has been shown that such correlations could be used to build entangled states of electrons [11,12]. If the probe electrodes are ferromagnetic, the conductance due to these Crossed Andreev (CA) processes is sensitive to the relative magnetic polarization, being maximal for opposite polarization of the F probes [10].

In the present Letter, we investigate in detail the dependence of the conductance on the distance between the probes and on their spin polarization. We consider a three-terminal device $A/S/B$ (see Fig.1a) where S is an s-wave superconductor and the electrodes A and B can be either normal metals or ferromagnets. We study the linear conductance matrix at subgap temperature and voltages (the subgap regime $T, eV_i \ll \Delta$ is assumed in what follows). Then no single electron channel is left and all the relevant channels involve simultaneous (on a time $\sim \hbar/\Delta$) tunneling of two electrons or holes (Fig. 1b) : (a) single-contact Andreev reflection ($2A$ and $2B$), where two electrons, both originating from the same electrode, A or B , are converted in a Cooper pair giving rise to the currents $G_{2A}V_A$ and $G_{2B}V_B$; (b) CA processes, where two electrons, each originating from a different A/B electrode are converted into a Cooper pair, with associated current $G_{CA}(V_A + V_B)$ from each A/B probe to S ; (c) cotunneling (EC), which is easily visualized in the tunneling limit [13] as processes in which, for instance, an electron from A tunnels to B via a virtual state in S ; EC processes yield a current from A to B , $G_{EC}(V_B - V_A)$. Then the subgap currents can be presented in a matrix form

$$\begin{pmatrix} I_A \\ I_B \end{pmatrix} = \begin{pmatrix} G_{2A} + G_{CA} + G_{EC} & G_{CA} - G_{EC} \\ G_{CA} - G_{EC} & G_{2B} + G_{CA} + G_{EC} \end{pmatrix} \begin{pmatrix} V_A \\ V_B \end{pmatrix} \quad (1)$$

The multi-contact processes, CA and EC, increase the "diagonal" conductances $dI_A/dV_A, dI_B/dV_B$ and give rise to off-diagonal terms $dI_A/dV_B, dI_B/dV_A$, i.e. the current at probe A (B) depends also on the voltage at probe B (A). The generalization of Eq.(1) to more complicated structures (see Fig.1.c) is straightforward.

For illustrative purposes we calculate the conductance matrix for contacts being tunnel junctions. The single-junction conductances G_{2A} and G_{2B} were calculated in Ref. [14]. Here we find that EC and CA conductances depend on the relative position $\vec{R}$ of the contacts, vanishing exponentially for $|\vec{R}| \gg \xi$. For multichannel tunnel junctions they are found to depend on propagation in S in a way which is sensitive to the geometry of the sample. This is due to interference effects between different channels, which also play a role in determining the single-junction NS conductances [14]. In multichannel junctions with normal A/B electrodes we find $G_{CA} = G_{EC}$, thus the off-diagonal terms in the conductance matrix Eq.(1) vanish. This symmetry is broken if A/B are polarized ferromagnets. Indeed G_{EC} is suppressed if A and B have opposite polarization, because EC processes preserve the spin of the involved electron (in absence of any magnetic scattering whatsoever) and take advantage from parallel A/B polarization. On the other hand CA tunneling is suppressed for parallel A/B polarization since it is difficult to find two partner electrons with opposite spin to pair up. Then if magnetically polarized probes are used, off-diagonal conductances in Eq.(1) are non vanishing, due to the presence of unbalanced CA and EC processes, for inter-contact distance $|\vec{R}| \lesssim \xi$.




Fig. 1 – (a) Schematics of the three-terminal A/S/B device; (b) diagrammatic representation of the processes leading to subgap conductance: single-contact two-particle tunneling (2A and 2B), elastic cotunneling (EC), which probes the normal Green’s function (full lines) of S and “crossed Andreev” (CA), which probes the anomalous propagator (dashed line); (c) a simple experimental design for measuring the excess EC and CA currents: various electrodes (A, B, C, D, E) allow to probe different distances $\vec{R}_{ij}$.

Cotunneling and Crossed Andreev tunneling rates. – We describe contacts in the tunneling regime by standard tunneling Hamiltonians

$$\mathcal{H}_{TA} = \sum_{kp\sigma} T_{kp}^A c_{k\sigma}^\dagger d_{p\sigma} + T_{kp}^{(A)*} d_{p\sigma}^\dagger c_{k\sigma} \quad ; \quad \mathcal{H}_{TB} = \sum_{pq\sigma} T_{pq}^B d_{p\sigma}^\dagger c_{q\sigma} + T_{pq}^{(B)*} c_{q\sigma}^\dagger d_{p\sigma} \quad (2)$$

where T_{kp}^A and T_{qp}^B are matrix elements between single electron states $k \in A$, $p \in S$ and $q \in B$. Quasiparticle states in S are defined by the operators $\gamma_{p\sigma} = u_{p\sigma} d_{p\sigma}^+ - v_{p\sigma} d_{-p-\sigma}$.

We now classify processes which appear in perturbation theory in $\mathcal{H}_{Ti}$. Single electron processes are absent in the subgap regime. In lowest nonvanishing order we have to consider only “elastic” processes, where the quasiparticle created in the intermediate state is destroyed [13]. “Inelastic” processes leave an excitation of energy $\gtrsim \Delta$ in the superconductor, so under subgap conditions they can be neglected. The relevant processes, represented in Fig.1b, are single-contact Andreev reflection in the tunneling limit (2A and 2B) [14], CA tunneling, and “elastic” cotunneling [13], where *the same* electron tunnels at once from A to B (B to A). One notices that EC and CA are non-local probes of electron propagation in the superconductor [9]. This is apparent if one considers the gedanken case of single channel tunnel junctions, where the size of the contacts is $d_A, d_B \sim \lambda_F$, the Fermi length. EC probes the “normal” propagator in the superconductor whereas CA processes probe the *anomalous* propagator (see Fig.1b) and both processes are exponentially suppressed for $R \gg \xi$.

We now turn to the calculation of the spin dependent tunneling rates, using Fermi’s golden rule. We consider electrodes A and B which can be magnetically polarized (parallel or antiparallel) along the same axis, resulting in different spectral properties. We neglect here the influence of ferromagnetic electrodes on the superconductor’s spectrum. This a reasonable

assumption for small tunneling contacts on a massive superconductor. In this case, the proximity effect should not be too serious, e. g. superconductivity is not destroyed in the contact vicinity. This is in contrast with Ref. [15] where a sandwich geometry is considered, and where conduction above the gap is studied.

By proceeding along the lines of Ref. [14] we write the EC rate $A\sigma \rightarrow B\sigma$ as

$$\Gamma_{A \rightarrow B}^\sigma = \frac{2\pi}{\hbar} \int d\varepsilon d\varepsilon' d\zeta d\zeta' \delta(\varepsilon - \varepsilon') f(\varepsilon - eV_A) [1 - f(\varepsilon' - eV_B)] \\ F_{EC}(\zeta, \varepsilon) F_{EC}(\zeta', \varepsilon') \Xi_{EC}^\sigma(\varepsilon - eV_A, \varepsilon' - eV_B, \zeta, \zeta') \quad (3)$$

where $f(\varepsilon)$ is the Fermi function, $F_{EC}(\zeta, \varepsilon) = (\zeta + \varepsilon)/(\zeta^2 + \Delta^2 - \varepsilon^2)$ contains information on energies of virtual quasiparticles in S . The rate for CA processes, $(A\sigma, B - \sigma) \rightarrow S$, is given by a similar expression

$$\Gamma_{AB \rightarrow S}^\sigma = \frac{2\pi}{\hbar} \int d\varepsilon d\varepsilon' d\zeta d\zeta' \delta(\varepsilon + \varepsilon') f(\varepsilon - eV_A) f(\varepsilon' - eV_B) \\ F_{CA}(\zeta, \varepsilon) F_{CA}(\zeta', \varepsilon') \Xi_{CA}^\sigma(\varepsilon - eV_A, \varepsilon' - eV_B, \zeta, \zeta') \quad (4)$$

where $F_{CA}(\zeta, \varepsilon) = \Delta/(\zeta^2 + \Delta^2 - \varepsilon^2)$. Information about propagation in the specific geometry are contained in the functions $\Xi(\varepsilon, \varepsilon', \zeta, \zeta')$. Here we give the explicit expression for planar uniform tunnel junctions and local tunneling, $T(\vec{r}, \vec{r}') = T \delta(z) \delta(\vec{r} - \vec{r}')$. We moreover consider ballistic propagation of plane wave states (generalization to diffusive conductors can be made following Ref. [14]). In this case the functions Ξ_{EC} and Ξ_{CA} can be expressed as

$$\Xi_{EC}^\sigma(\varepsilon, \varepsilon', \zeta, \zeta') = |T_A T_B|^2 \int_A d\vec{r}_1 d\vec{r}_2 \int_B d\vec{r}_3 d\vec{r}_4 J_A^\sigma(12, \varepsilon) J_S^\sigma(31, \zeta) J_S^\sigma(24, \zeta') J_B^\sigma(43, \varepsilon') \quad (5) \\ \Xi_{CA}^\sigma(\varepsilon, \varepsilon', \zeta, \zeta') = |T_A T_B|^2 \int_A d\vec{r}_1 d\vec{r}_2 \int_B d\vec{r}_3 d\vec{r}_4 J_A^\sigma(12, \varepsilon) K_S^\sigma(31, \zeta) K_S^{*\sigma}(24, \zeta') J_B^{-\sigma}(43, \varepsilon')$$

where the spectral functions are defined as, e.g. $J_A^\sigma(12, \omega) \equiv J_A^\sigma(\vec{r}_1, \vec{r}_2, \omega) = \sum_{\mathbf{k}} \delta(\omega - \varepsilon_{\mathbf{k}\sigma}) \psi_{\mathbf{k}\sigma}(\vec{r}_1) \psi_{\mathbf{k}\sigma}^*(\vec{r}_2)$, $K_S^\sigma(31, \omega) \equiv K_S^\sigma(\vec{r}_3, \vec{r}_1, \omega) = \sum_{\mathbf{k}} \delta(\omega - \varepsilon_{\mathbf{k}\sigma}) \psi_{-\mathbf{k}-\sigma}(\vec{r}_3) \psi_{\mathbf{k}\sigma}(\vec{r}_1)$. The space integrals in (5) run on the contact surfaces. The diagrammatic representation is given in Fig. 1.b.

At low temperature and voltages the main contribution to the rates Eqs.(3,4) is due to electrons close to the Fermi level in the A/B probes, $\varepsilon = \pm\varepsilon' \approx 0$, and the leading dependence of the rates on the voltages comes from the Fermi functions. One can let $\Xi(\varepsilon, \varepsilon', \zeta, \zeta') \approx \Xi(0, 0, \zeta, \zeta')$ and perform the ε and ε' integrations in Eqs.(3,4). At $T = 0$ this gives $I_{EC}^\sigma = e\Gamma_{A \rightarrow B}^\sigma = G_{EC}^\sigma(V_B - V_A)$ and $I_{CA}^\sigma = 2e\Gamma_{AB \rightarrow S}^\sigma = 2G_{CA}^\sigma(V_A + V_B)$, which define the spin-dependent conductances.

It is instructive to consider first single channel junctions ($d_A, d_B \sim \lambda_F$). The conductances are calculated by putting $\vec{r}_1 = \vec{r}_2$, $\vec{r}_3 = \vec{r}_4$, $\vec{r}_1 - \vec{r}_3 = \vec{R}$ in Eq.(5). By performing the ζ and ζ' integrations the result is obtained

$$\begin{pmatrix} G_{EC}^\sigma \\ G_{CA}^\sigma \end{pmatrix} \approx \frac{2\pi^3 e^2}{\hbar} |T_A d_A|^2 |T_B d_B|^2 N_S^2(0) N_A^\sigma(0) \frac{e^{-2R/\pi\xi}}{(k_S R)^2} \begin{pmatrix} N_B^\sigma(0) \cos^2(k_S R) \\ N_B^{-\sigma}(0) \sin^2(k_S R) \end{pmatrix} \quad (6)$$

where k_S and $N_S(0)$ are the Fermi wavevector and the normal state density of states of the superconductor. Propagation in the superconductor is characterized by factors which depend on $|\vec{R}|$, being periodic with period π/k_S and being suppressed for $|\vec{R}| \gg \xi$. The magnetic polarization of A/B electrodes enters only via the spin-dependent density of states

$N_{A,B}^\sigma(0)$, assuming that $N_{A,B}^\sigma(0) = N_{A,B}^0(\pm\mu h)$ where h is the exchange field, $N_{A,B}^0$ is the density of states in absence of magnetism and $\mp$ sign stands for spin σ (anti)parallel to the magnetization. If the density of states for minority spin can be neglected, then for parallel (antiparallel) polarized contacts only EC (CA) processes will yield a conductance.

For the more realistic case of multichannel tunnel junctions, interference between different channels has to be considered. This has been studied in Ref. [14] for single contact processes (A1 and A2) in a NS tunnel junction, which probe propagation in the *normal* electrode (it is in general diffusive and depends on the geometry). As for EC and CA, we notice that in clean superconductors the single particle propagator is rapidly oscillating ($\sim k_S$), so it would average out on a length $\xi \ll 1/k_S$ in multichannel junctions. This is not the case for two-particle propagators involved in EC and CA processes, as we show explicitly below by considering a specific geometry.

At this stage one could assume that the overall conductance is given by independent single-channel contributions, start from Eq.(6) and argue that the factors $\cos^2(k_S R)$ and $\sin^2(k_S R)$ are averaged over distances $\sim d_A, d_B$. The resulting expressions for the EC and CA conductances would be nearly identical yielding, in the special case of normal A/B electrodes, $G_{EC} = G_{CA}$. This conclusion turns out to be correct, even if the actual expression for the conductances involves interference between different channels. To show that we start the calculation from Eq.(5), accounting also for different spin-dependent Fermi wavevectors k_A^σ (k_B^σ) of the A (B) electrode and k_S . We perform the coordinate integrations, and at this stage it becomes apparent that the terms leading to the special dependence $\cos^2(k_S R)$ and $\sin^2(k_S R)$ drop out. Because of interference between different channels, the result depends on the geometry and on the mismatch between the spin-dependent Fermi wavevectors. The simplest case is a geometry with the two junctions belonging to the same plane (see Fig.1a), where the results depend on the distance $R > d_A, d_B$

$$\begin{pmatrix} G_{EC}^\sigma \\ G_{CA}^\sigma \end{pmatrix} \approx \frac{h}{8e^2} \mathcal{F}_A^\sigma G_A^\sigma \begin{pmatrix} \mathcal{F}_B^\sigma G_B^\sigma \\ \mathcal{F}_B^{-\sigma} G_B^{-\sigma} \end{pmatrix} \frac{e^{-2R/\pi\xi}}{(k_S R)^2} \quad (7)$$

Here the factors $\mathcal{F}_{A,B}^\sigma$ contain information on the geometry and $G_{A,B}^\sigma$ are the spin-dependent one-electron conductances for each junction (S being in the normal state), for instance

$$G_A^\sigma \approx \frac{4\pi e^2}{h} N_A^\sigma(0) N_S(0) \frac{|T_A|^2 \mathcal{S}}{k_A^\sigma k_S} \mathcal{F}(\kappa_A^2, \sqrt{k_S k_A^\sigma} d_A) \quad (8)$$

where $\kappa_{A,B} = (k_{A,B}^\sigma/k_S)^{1/2}$ and $\mathcal{S}$ is the area of the junction. Here the single junction geometry factor is given by $\mathcal{F}(\kappa^2, y) = 2\pi \int_0^y (dx/x) \sin(\kappa x) \sin(x/\kappa)$ and the two-junction factors in Eq.(7) are, e.g., $\mathcal{F}_A = [\mathcal{F}(\kappa_A^2, \sqrt{k_S k_A} d_A)]^{-1} \mathcal{R}e \int_0^{2\pi} d\theta [1 - e^{ik_S d_A (\kappa_A^2 + \cos \theta)}] / (\kappa_A^2 + \cos \theta)$ for the geometry we consider. It is important to point out only some general property. For $\kappa = 1$ the factor $\mathcal{F}(1, y) \propto \ln y$ depends weakly [16] on the reduced size y ; the factors $\mathcal{F}_{A,B}$ are even more weakly dependent on y and substantially of order one. A slight asymmetry $\kappa \neq 1$ makes all the factors $\mathcal{F}$ independent on the size of the junctions, if d_A, d_B are large enough, $y|\kappa - \kappa^{-1}| \gg 1$. Still $\mathcal{F}_{A,B}$ are of order one, so EC and CA processes determine an appreciable conductance.

Discussion. – We can now discuss the full conductance matrix in equation (1) by defining the total EC and CA conductivities $G_{EC} = G_{EC}^\sigma + G_{EC}^{-\sigma}$ and $G_{CA} = G_{CA}^\sigma + G_{CA}^{-\sigma}$. The EC and CA conductances appear both in the diagonal and in the off-diagonal conductance matrix elements in Eq.(1). Let us first consider the case of non magnetic contacts, where we can drop

the spin dependence. For multichannel contacts Eq.(7) shows that $G_{EC} = G_{CA}$, so the off diagonal conductances *vanish*. Coherent tunneling processes involving two distant contacts enter only the diagonal terms, and provide as an extra contribution with respect to the standard Andreev conductances G_{2A} and G_{2B} . The extra current depends on the distance R between the two contacts. A simple setup where the R dependence of the extra current can be studied is shown in Fig.1c (alternatively one may use a STM tip as a mobile contact). Another signature of CA and EC processes can be found if one considers contacts of very different transparency, say $|T_A| \gg |T_B|$. In this case $G_{2A} \propto |T_A|^4$ dominates $G_{EC} + G_{CA} \propto |T_A|^2 |T_B|^2$, which itself is much larger than $G_{2B} \approx |T_B|^4$. Thus the conductance at the less transparent probe (lower right diagonal element in Eq.(7)) is given by $G_{EC} + G_{CA}$, so it is essentially due to two-contact processes: if we bias contact B a current will flow because of correlations of superconductive nature with contact A . If $R < \xi$, the crossed conductances are still affected by the factor $(k_S R)^{-2}$ which can be very small [12]. This problem can be partially overcome for instance by choosing one contact A to be of size $d_A \gg \xi$ or even a semi-infinite interface.

Let us now consider the case of spin polarized probes. As it is apparent from Eq.(7) $G_{EC} \neq G_{CA}$ so the off diagonal elements in the conductance matrix, Eq.(1), are finite and the current in one contact can be manipulated by the voltage bias of the other contact. The sign of this effect depends on the mutual polarization of the electrodes. This generalizes the result of Ref. [10]. More in detail, spin polarization enters in two ways in the result (6,7): first, in the spin-dependent densities of states; second, in the shift of the Fermi momenta $k_{A,B}^\sigma$, which modifies the factors $\mathcal{F}$ in Eqs.(7). To fix the ideas, let us for simplicity neglect the latter and concentrate on the effect of the density of states. Defining the contact polarizations $P_{A,B} = \frac{N_{A,B}^\sigma - N_{A,B}^{-\sigma}}{N_{A,B}^\sigma + N_{A,B}^{-\sigma}}$, one has simply that G_{EC} is proportional to $(1 + P_A P_B)$ and G_{CA} to $(1 - P_A P_B)$. Therefore the off-diagonal conductance is roughly proportional to $(-P_A P_B)$. This shows a striking consequence of the competition between cotunneling and crossed Andreev processes, via their spin-dependence: not only the amplitude, but also the sign of the conductances can be controlled by spin polarizations. In the extreme case of parallel complete polarizations the only possible process is cotunneling, with $I_A = -I_B$, while for antiparallel polarization crossed Andreev tunneling prevails, with $I_A = I_B$.

So far we have discussed the zero-temperature case. Direct generalization to finite temperature leads formally to a divergence of the tunneling rate. It is due to the finite, though very small ($\propto e^{-\Delta/T}$), probability of exciting an electron from $A(B)$ to a quasiparticle state in S , and to the divergence of the quasiparticle density of states in S . The divergence in the rates disappears if the latter is rounded off at Δ . The EC and CA conductances acquire an additional contribution $\propto e^{-\Delta/T} \ln(\Delta/\Gamma)$ where Γ is a scale related to the mechanism of broadening of the quasiparticle levels in the superconductor.

In the present Letter we have demonstrated the non-local character of cotunneling and Andreev reflections on a superconductor and we have also studied the role of magnetic polarization. We have discussed possible schemes to detect these effects in devices with three or more terminal. Devices with high transparency contacts [10] are also promising for experiments. Further theoretical analysis would require the self-consistent analysis of the mutual effects of superconductivity, diffusive propagation and ferromagnetism in the hybrid system. For both high and low transparency contacts propagation in the specific geometry has to be taken into account.

* * *

One of the authors (D. F.) is grateful to Prof. G. Deutscher for stimulating discus-

sions. G.F. acknowledges discussions with R. Fazio, support and hospitality by LEPES-CNRS Grenoble (France), and support from MURST-Italy (Cofinanziamento SCQBD), INFM (PAIS-ELMAMES) and EU (grant TMR-FMRX-CT-97-0143).

REFERENCES

- [1] A. F. Andreev, Sov. Phys. JETP **19**, 1228 (1964) (Zh. Eksp. Teor. Fiz. **46**, 1823 (1964)).
- [2] G. E. Blonder, M. Tinkham and T. M. Klapwijk, Phys. Rev. **B25**, 4515 (1982); G. E. Blonder and M. Tinkham, Phys. Rev. **B27**, 112 (1983).
- [3] M. J. M. de Jong and C. W. J. Beenakker, Phys. Rev. Lett. **74**, 1657 (1995).
- [4] R. J. Soulen Jr, J. M. Byers, M. S. Osofsky, B. Nadgorny, T. Ambrose, S. F. Cheng, P. R. Broussard, C. T. Tanaka, J. Nowak, J. S. Moodera, A. Barry and J. M. D. Coey, Science **282**, 85 (1998).
- [5] S. K. Upadhyay, A. Palanisami, R. N. Louie and R. A. Buhrman, Phys. Rev. Lett. **81**, 3247 (1998).
- [6] M. Giroud, H. Courtois, K. Hasselbach, D. Mailly, and B. Pannetier, Phys. Rev. B **58**, 11872 (1998).
- [7] V.T. Petrashov, I.A. Sosnin, I. Cox, A. Parsons, and C. Troadec, Phys. Rev. Lett. **83**, 3281 (1999).
- [8] C. J. Lambert and R. Raimondi, J. Phys. Condens. Matter **10**, 901 (1998).
- [9] J. M. Byers and M. E. Flatté, Phys. Rev. Lett. **74**, 306 (1995).
- [10] G. Deutscher and D. Feinberg, Appl. Phys. Lett. **76**, 487 (2000).
- [11] G. B. Lesovik, Th. Martin and G. Blatter, ArXiv:cond-mat/0009193.
- [12] M. S. Choi, C. Bruder and D. Loss, Phys. Rev. **B62**, 13569 (2000); P. Recher, E. V. Sukhorukov and D. Loss, ArXiv:cond-mat/0009452.
- [13] D.V. Averin and Yu.V. Nazarov, in *"Single Charge Tunneling"*, Chap. 6, ed. by H. Grabert and M.H. Devoret, Plenum Press, New York 1992.
- [14] F.W.J. Hekking and Yu.V. Nazarov, Phys. Rev. **B49**, 6847 (1994).
- [15] S. Takahashi, H. Imamura and S. Maekawa, Phys. Rev. Lett. **82**, 3911 (1999).
- [16] F.W.J. Hekking in "Coulomb and interference effects in small electronic structures", edited by D.C. Glatthli, M. Sanquer and J. Trân Thanh Vân (Edition Frontières, Gif-sur-Yvette, France, 1994).